

Building Life

RD1203S Standalone Reader

Product Features

- Standalone type, combine 125K RF reader and access controller without pc operation.
- Two sets of output contact for electric lock (NO and NC).
- Capacity:1000 cardholders.
- Single card , batch card and all user card add (delete) possible.
- Two type of master card for ENCODING CARD and DELETING CARD,..
- Two sets of input point, for sensor and push button.
- Double LED indicator , door open time adjustable from1-99 sec.
- Use RS232 connect to PC to delete card and set strike duration.
- Enclosure housing tamper alarm.



產品規格

Input voltage : 12Vdc±10%
Consumption current : 2A
Operate frequency: 125K

Read Range: Over 10cm
Operation Temperature : -40°C ~ +85°C
SIZE : 115L x 74W x 15H mm



立固自動化系統股份有限公司
LEEGOOD AUTOMATIC SYSTEMS, INC.
地址/台北縣三重市重新路五段609巷4號6樓之6